

How do I setup the A/V Input?

Note: The DP-P2 has input ports that allow you to connect another A/V device – like a Foxtel STB so you can record it. The DP-P2 can pass the signal through to the TV when it is in standby so you don't need to disconnect it.

1. The back of the DP-P2 has input ports for **Composite** or **S-Video** as well as **Left** and **Right** audio.
Connect the **Composite** (Yellow) or **S-Video** cable from the Output ports of your input device (ie PayTV STB) cables to the same **INPUT** port on the Beyonwiz PVR. Then connect the **Left** (white) and **Right** (Red) ports of your input device (ie Foxtel STB) cables to the same **INPUT** ports on the DP-P2.
2. Switch on the DP-P2 and wait for a picture to show on the screen. If a picture doesn't appear, your PVR may need to scan your channels first – See "How do I do a Channel Scan?"
3. Press the **SETUP** button on the remote
4. Using the **ARROW** keys on the remote, navigate to the **Config** option on the top bar.
5. Make sure the highlighted item is **A/V Input** (left column) and press **OK** on the remote – the highlighted item should now be **A/V Input**.
6. Use the **ARROW** keys to highlight **>Enable**, and then press the **OK** button on the remote.



Note: This will create a new service (channel) called 950 A/V Input in the service list. This is the channel you need to select for recording via the A/V Input.

7. Use the **ARROW** keys to highlight **Display**, and then press the **OK** button on the remote and select Full or Centre for the display mode, then press the **OK** button.
8. Use the **ARROW** keys to highlight **Input**, and then press the **OK** button on the remote and select either Composite or S-Video, then press the **OK** button.
9. Use the **ARROW** keys to highlight **Video Type**, and then press the **OK** button on the remote and select either PAL or NTSC, then press the **OK** button.

Note:

*Pressing the **AV bypass** button on the remote when the DP-P2 is in **operating** mode will enable and disable the **pass through** feature.*

*To record from the A/V input, create a timer and select **950 A/V** as the service. You will need to configure your external device (ie Foxtel STB) to be on the appropriate channel at the right time for the DP-P2 to record from it.*

Cool Tip: If you have old videos or a video camera, you can convert them to digital using the A/V input!

FOR MORE DETAILED INFORMATION REFER TO PAGE 12 AND 30 OF THE MANUAL